

Eaton 189885

Catalog Number: 189885

Eaton Moeller® series PKZM01 Motor-protective circuit-breaker, 660 V 690 V: 1.1 kW, I_r= 1 - 1.6 A, IP20



Fotografia este reprezentativa

General specifications

| | |
|---|-----------------------|
| Product Name | Catalog Number |
| Eaton Moeller® series PKZM01 Motor-protective circuit-breaker | 189885 |
| | EAN |
| | 4015081878819 |
| Product Length/Depth | Product Height |
| 93 mm | 90 mm |
| Product Width | Product Weight |
| 45 mm | 0.292 kg |
| Compliances | Model Code |
| CE Marked | PKZM01-1,6-EA |
| RoHS conform | |

Caracteristici & funcții

Actuator type

Push button

Functions

Phase failure sensitive

Number of poles

Three-pole

Tensiune nominală

Rated operational power at AC-3, 220/230 V, 50 Hz

0.25 kW

Rated operational power at AC-3, 380/400 V, 50 Hz

0.55 kW

Rated operational voltage (Ue) - min

440 V

Rated operational voltage (Ue) - max

440 V

Rated uninterrupted current (Iu)

1.6 A

Grad de protecție la scurtcircuit

Short-circuit current rating (group protection)

50 kA, 600 V High Fault, Fuse, SCCR (UL/CSA) with 600 A, 600 V High Fault, Fuse, SCCR (UL/CSA)

50 kA, 600 V High Fault, CB, SCCR (UL/CSA) with 600 A, 600 V High Fault, CB, SCCR (UL/CSA)

Bloc de declanșare

Overload release current setting - min

1 A

Overload release current setting - max

1.6 A

Resurse

Characteristic curve

[eaton-manual-motor-starters-characteristic-characteristic-curve-008.eps](#)

[eaton-manual-motor-starters-characteristic-characteristic-curve-006.eps](#)

Instrucțiuni de instalare

IL034045ZU